

# Fujitsu T3000D Tablet PC

For more information about the Fujitsu Lifebook T3000D Tablet PC, contact Brian Moeggenberg of GSC Mobile Solutions at 800.333.9366 x124 or via email at [info@gscmobile.com](mailto:info@gscmobile.com). Be sure to let Brian know that you are a ChartingPlus client!



The image shows a silver Fujitsu LifeBook T3000D Tablet PC. The device is shown in two configurations: as a tablet with the screen folded up, and as a laptop with the screen folded down and the keyboard visible. The word "LifeBook" is written vertically in large, grey, sans-serif font on the left side of the image. The text "T3000D Tablet PC" is written in red at the top left of the image area.

- Convertible for notebook and tablet use
- 12.1" XGA display with active digitizer
- Wireless LAN, modem and Ethernet
- Lightweight and long battery life

The flexibility you've come to expect from Fujitsu. A tablet for on-the-spot note taking and drawing with digital ink. All combined with the full functionality of a notebook.

## Microprocessor

Intel® Pentium® M processor 1.40 GHz which supports enhanced Intel Speedstep™ technology, 1 MB on die L2 cache, 400 MHz system bus speed, 32-bit architecture

## Display

12.1" XGA display with electromagnetic (active) digitizer

## Chipset

Intel 855GM

## System Memory<sup>1</sup>

256 MB on board, two DIMM slots available; upgrade with 256 MB, 512 MB, or 1 GB SDRAM; maximum memory to 2 GB (1 GB x 2)

## Hard Drives

60 GB or 40 GB ATA 100, shock-mounted hard drive

## Video Controller

Intel 855GM video graphics chip with integrated 32-bit 3D/2D gfx core delivering low power high performance extreme graphics with AGP support  
Dynamic Video Memory Technology (DVMT) dynamically responds to application requirements and efficiently allocates up to 64 MB of system memory for optimal graphics and system performance

Maximum internal display resolution: 1024x768, 16M colors  
External monitor: 1600x1200 resolution, 16M colors  
Simultaneous and dual support for external monitor and internal display

## Audio

RealTek ALC202 with 16-bit stereo audio with built in microphone and headphone jacks

## Communications

Optional 802.11b/g™ wireless LAN with dual diversity antenna; up to 54 Mbps transfer rate; backward compatibility with 802.11b.  
Multinational<sup>3</sup> 56K4 V.90 modem and 10/100 Base-Tx Ethernet

## System Ports

2 USB 2.0  
Modem (RJ-11)  
Ethernet (RJ-45)  
VGA-out  
Infrared (IrDA-compatible, 4 Mbps)  
Headphone and microphone  
Docking port

## Security

Kensington™ lock slot, embedded Smart Card Reader, LifeBook Security Application Button panel

## PC Card Slot

Two Type II or one Type III slot  
32-bit PC CardBus architecture; embedded Smart Card Reader

## Battery / Life

Lithium ion / Up to 4.5 hours<sup>5</sup> with high-capacity main battery

## AC Adapter

Auto sensing dual voltage support  
100-240V AC; DC 16V, 3.75A

## Operating System

Microsoft® Windows XP Tablet PC Edition

## Bundled Software

Adobe Acrobat Reader, PowerQuest® Drive Image™ Special Edition, Microsoft® Internet Explorer, Fujitsu Hot Key Utility, MS Reader, NewsStand Reader, Zinio Reader, Franklin Covey Tablet Planner 30-day Free Trial and high-capacity main battery

## Warranty

One-year International Limited Warranty<sup>6</sup>, upgradable to three years  
24 x 7 technical support  
Fujitsu Premium Care service plans available

## Accessories

Visit [www.fujitsupc.com](http://www.fujitsupc.com) or call 1-877-372-3473 for a complete listing of Fujitsu accessories.

<sup>1</sup>In order to upgrade your memory to 512 MB, remove the 256 MB memory module.

<sup>2</sup>Accessible capacity may be less due to formatting, applications, and backup utilities. For maximum user convenience and confidence, 1.5 GB of the drive is partitioned and the original factory image is stored there. PowerQuest® Drive Image® Special Edition, a system recovery utility, can be used to restore the computer to its original state at any time.

<sup>3</sup>The internal modems on all Tablet PCs from Fujitsu PC Corporation are only qualified for use with telephone systems in selected countries, including the United States and Canada. For a list of certified countries, please [www.fujitsupc.com/modems](http://www.fujitsupc.com/modems)

<sup>4</sup>Actual speeds over U.S. telephone lines vary, and are less than 56 Kbps due to current FCC regulations and line conditions.

<sup>5</sup>Battery life estimates reflect the results of Ziff Davis Business Winstone 2001 BatteryMark 1.0 as performed upon systems with maximum battery life setting enabled. Actual battery life will vary based on screen brightness, applications used, features selected, power management settings, battery conditioning, and other customer preferences. DVD/CD-RW, wireless LAN, LAN or hard drive usage may also have a significant impact on battery life. Requires optional high-capacity battery and optional second bay battery for optimal battery life.

<sup>6</sup>Service and warranty turnaround time may vary by country and product. International warranty valid only for products purchased in North, Central, and South America.